



BEAMZ
MADE
EAZY

150.612 V1.1

COB150 WW

QUICK START GUIDE

CONTROL MENU

MENU		DESCRIPTION	
DMX MODE	DMX	04CH	ADDR:001-512
		02CH	
		01CH	
AUTO	AUTO	01-04	Auto program
SOUND	SOUND	01-03	Sound Program
SPEED	SPEED	01-09	Speed
MIC SENSITIVITY	SENSITIV	01-09	MIC sensitivity
EDIT COLOR	COLOR	Ww:000-255	Warm white (0-100%)
DIMMING	DIMMING	01-99	Master dimming
FADING	FADING	00-99	Fading Program
FLASH	FLASH	00-99	Flash Program
SILENT SCENE	SILENT	ON/OFF	Silent scene by Sound program
SLAVE	SLAVE	SLAVE MODE	Enable slave mode
INFRARED	INFRARED	ON/OFF	Enable or Disenable IR remote

DMX CHANNELS

1 CH MODE

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	Color	000-255	Warm white (0-100%)

2 CH MODE

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	Dimmer	000-255	Master dimming (0-100%)
2	Strobe	000-009	No function
		010-255	Stroboscope (Rate 0-100%)

4 CH MODE

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	Dimmer	000-255	Master dimming (0-100%)
2	Strobe	000-009	No function
		010-255	Stroboscope (Rate 0-100%)
		040-069	Auto program2 (rate)
		070-099	Auto program3 (rate)
3	Color	000-255	Warm white (0-100%)
4	Auto	000-009	No function
		010-039	Auto program1
		040-069	Auto program2 (rate)
		070-099	Auto program3 (rate)
		100-129	Auto program4 (rate)
		130-159	Sound program1 (rate)
		160-189	Sound program2 (rate)
190-255	Sound program3 (rate)		



A series of horizontal dotted lines for writing, spanning the width of the page.





BEAMZ

YOUR FUTURE
YOUR SKILLS
YOUR PLATFORM
YOUR PARTY
YOUR EVENT



offers a wide range of high performance lighting equipment and related accessories for the rental, entertainment and architectural lighting markets. BeamZ Pro stands for performance, innovation and value pricing!

